



XDS Pro 4Q AES/EBU Digital Audio Output

The PRO 4Q receiver has four digital audio output channels that provide AES/EBU versions of the four analog audio output ports A through D. The channels are mapped from analog Port A to the digital pair of CH0 signals, Port B to CH1, Port C to CH2, and Port D to CH3. The following tables contain the interface specifications and connector pin-out of the digital audio port.

Connector	DB-9 Male
Format	Balanced AES/EBU

PIN	FUNCTION
1	CH0_TX+
2	CH1_TX+
3	Ground
4	CH2_TX+
5	CH3_TX+
6	CH0_TX-
7	CH1_TX-
8	CH2_TX-
9	CH3_TX-