



Instructions for Downloading Commercial Content from the XDS Pro Receiver

You will need the IP Address of that receiver. You can get it from the front panel of the receiver by using the keypad and going to Setup > Network > LAN Address. Then browse to the address on a PC on your network:

Setup Network

LAN Address 10.10.19.160
(example)

A screenshot of a browser's address bar. The text "Address" is on the left, and "http://10.10.19.160/" is entered in the input field.

After you enter the IP Address on your browser, you will see the receiver's log in screen:

Log in to make changes to your receiver's settings.

A screenshot of a login form. It has two input fields: "Username:" and "Password:". Below the fields is a "Login" button.

Login info:

Username: **tech**

Password: Use your Affiliate NMS (myxdsreceiver.cmneng.com) password OR you can use the receiver's daily password (Setup > Serial # > PWD).

Once you are in the receiver's status screen, click on the **Content** tab:

A screenshot of a navigation bar with three tabs: "General", "Programming", and "Content". The "Content" tab is highlighted.









Once you are in the Content area, click on the **Audio** or **All** tab:

A screenshot of a sub-navigation bar with two tabs: "Audio" and "All". The "Audio" tab is highlighted.

Once you are in the chosen area, you will see a list of all the commercial content saved on the receiver.

Audio Content

Title Filter Show All Currently showing: 171/171

	Title ▾	ISCI	⊕ Packages	Received
	----ECON GROUP----(WW TA-CHING7500)	WW_TA-CHING7500		2016-02-10
	A PLACE FOR MOM(WW PFM3S3950633)	WW_PFM3S3950633		2016-09-16
	ADVANC VCAS EST 449 - 4957(YSR QAPT5050R)	YSR_QAPT5050R		2016-08-28
	ADVANC VCAS EST 449(TDR QAPT5050R)	TDR_QAPT5050R		2016-09-15
	ADVANCE AUTO PARTS(WW QAPT5024R000)	WW_QAPT5024R000		2016-08-19
	AMERICAS BEST VALUE INN(CM ABVIVHFSRP30)	CM_ABVIVHFSRP30		2016-09-07
	ANHEUSER BUSCH(WW BW6016300000)	WW_BW6016300000		2016-09-16
	ASUS(WW ASUSNYCBNHRV)	WW_ASUSNYCBNHRV		2016-09-02

You can save any of the recorded files by using the "Right Click / Save As" method and saving them to a file on the PC. You can now use the saved files as you see fit.

NOTE: If your XDS receiver has DHCP enabled, the IP Address **WILL** change if the receiver is rebooted and will need to be retrieved again.

If ISCI's are missing in the Commercial Schedule, station staff can find them in the Traffic Instructions.

In the event of any problems or questions, please contact **Westwood One Technical Services**, 9AM – 7PM Eastern Time, Mon – Fri:

Phone: (914) 908-3210
Fax: (914) 305-9846
E-mail: techservices@westwoodone.com